



City of San Dimas

Building and Safety Division

Phone: (909) 394-6260 E-Mail: building@sandimasca.gov

Residential EV Charging Stations

Governing Code: 2025 California Electrical Code & City of San Dimas Municipal Code

Job Address: _____ Permit Number: _____

Scope of Work: _____

Requirements for Submittal:

(1) Electrical Application (3) Copies of Site Plan (2) Copies of this completed form

Please fill out the charts below by checking the items that apply to your project:												
Charger System or Outlet (must be within 25-feet of vehicle parking)			Overcurrent Protection Ampere-Rating (GFCI Protection Required)						Conduit Type			
Garage (Interior)		Exterior of Home		30	40	50	60	80	100	EMT	FMC	PVC
Main Panel Overcurrent Protection			Wire Size / EGC Size (Copper / AWG / THWN/THHN)					Conduit Size (inches)				
100 AMP	125 AMP	150 AMP	175 AMP	200 AMP	10 / 10	8 / 10	6/10	4/8	3 / 8	¾	1	1.25

**As an alternate, Nonmetallic Sheathed Cable (aka: ROMEX Cable or NMC) may be used if it is installed in interior locations only and protected from physical damage by placing the cable inside of the wall or attic space.

Sum of the Total Watts Used from Table on Sheet 2	Total Watts Used	Minimum Required Size of Main Panel Overcurrent Protection
	If up to 48,000 Watts	100 Amperes
	If greater than 48,000 up to 63,000 Watts	125 Amperes
	If greater than 63,000 up to 78,000 watts	150 Amperes
	If greater than 78,000 to 108,000 watts	200 Amperes
If greater than 108,000 watts then a full standard load calculation is required. Use of this form is not accepted.		

** Loads shown are rough estimates only; actual loads may vary – for a more precise analysis, consult with a trained electrical professional. This is not to be used to determine size of a new electrical service.

Check all Applicable Loads	Description of Load	Typical Usage	Watts Used
	Multiply square footage of the home by 3	3 watts/sq. ft.	
Kitchen Circuits			
	Kitchen Circuits	3,000 Watts	
	Electric Oven	3,000 Watts	
	Electric Stove Top	5,000 Watts	
	Microwave	1,500 Watts	
	Garbage Disposal – under kitchen sink	1,000 Watts	
	Automatic Dishwasher	3,500 Watts	
Laundry			
	Laundry Circuit	1,500 Watts	
	Electric Clothes Dryer	4,500 Watts	
Heating and Air Conditioning			
	Central heating (gas) and air conditioning	7,000 Watts	
	Central Electric Furnace	8,000 Watts	
	Whole house or attic fan	500 Watts	
	Electric water heater (tank storage type)	4,000 Watts	
	Swimming pool pump (each)	3,500 Watts	
	OTHER: (describe)		
Electric Vehicle Charger Circuit			
	Use nameplate rating in watts or calculate: (Ampere rating of circuit by 240 volts = Watts)		
Add up all of the watts for the loads listed above (total watts used): Transfer this number to the table on sheet 1 to determine the minimum required size of service.			

Please note that this electrical calculation is a voluntary compliance alternative and you may wish to hire a qualified individual or company to perform a thorough evaluation of your electrical service in lieu of this alternative methodology. Use of this electrical load calculation estimate and form is at the user's risk and carries no implied guarantee of accuracy. Users of this methodology and these forms are advised to seek professional assistance in determining the electrical capacity of the service panel.

By my signature, I attest that the information provided is true and accurate.

Signature: _____ Date: _____

Print Name: _____

SAMPLE SITE PLAN

